

Test Report for Charge Stations connected to GreenFlux Platform using OCPP1.6 via JSON	
Manufacturer Name:	Wallbox
Hardware model:	Supernova
Firmware	1.12.45
Tester:	Aneta Benova & Xavi Albert
Date:	10.2.2023

BASIC	Step	OCPP Profile	Action	Timestamp	Pass	Remarks
	1	Core	Boot charging station	2023-02-10	Y	firmware version and ICCID is not included in boot notifications
	2	Core	Change availability	2023-02-10	Y	
	3	Core	Get Configuration	2023-02-10	Y	
	4	Core	Change Configuration	2023-02-10	Y	
	5	Core	Heartbeat	2023-02-10	Y	
	6	Core	Charging Session - Local - Plugin first	2023-02-10	Y	
	7	Core	Charging Session - Local - Identification first - Connection Loss	2023-02-10	Y	
	8	Core	Charging session - Local - Identification first - Connection TimeOut	2023-02-10	Y	
	9	Core	Hard Reset - During Charging session	2023-02-10	Y	The ongoing transaction is stopped and boot notification is received. Only status of the charger is not changed to unavailable before the reboot.
	10	Core	Hard Reset - No charging session	2023-02-10	Y	See notes in step 9
	11	Core	Soft Reset - During Charging session	2023-02-10	Y	Soft reset works has the same implementation as hard reset.
	12	Core	Soft Reset - No charging session	2023-02-10	Y	See notes in step 9
	13	Core	Charging session - Local - Unauthorized	2023-02-10	Y	
	14	Core	Charging session - Remote Start and Stop Transaction - Cable first	2023-02-10	Y	
	15	Core	Charging session - Remote Start Transaction - Request first - Unlock Connector	2023-02-10	Y	Unlock connector command is not supported by DC chargers. Faulted message received, description of error codes will be implemented in Q2 2023
	16	Core	Hardware related notification / error condition	2023-02-10	Y	
	17	Firmware Management	Remote Firmware update - Download failed	2023-02-10	N	Charger doesn't check the location provided in UpdateFirmware request. Charger reaches to their own repository
	18	Firmware Management	Remote Firmware update - Installation failed	2023-02-10	N/A	
	19	Firmware Management	Remote Firmware update - Download & install	2023-02-10	Y	
	20	Firmware Management	Remote get diagnostics report		Y	
	21	Firmware Management	Remote get diagnostics - fail		Y	
	22	Core	Clear cache	2023-02-10	Y	
	23	Remote Trigger	TriggerMessage	2023-02-10	Y	