

Congratulations, you're certified!

You are now guaranteed compatibility
with the GreenFlux eMobility platform.



AUTEL®

Models

AC Ultra (Street)

Firmware Version

PFA0001|1.00.00|1.30.98|1.20.00|2.25.00|1.01.00

Certification date

27/05/2025

Certification level

- OCPP 1.6 JSON
- OCPP 2.0.1 Core
- Smart Charging 1.6 JSON
- Eichrecht



OCPP Integration Test Report



for Charge Stations connected to GreenFlux Platform using OCPP1.6 via JSON

Manufacturer Name: Autel
Hardware model: AC Ultra (Street)
Firmware: PFA0001|1.00.00|1.30.98|1.20.00|2.25.00|1.01.00
Tester: Malgorzata Guzel
Date: 27.05.2025

Step	OCPP Profile	Action	Pass	Remarks
1	Core	Boot charging station	Y	
2	Core	Change availability	Y	
3	Core	Get Configuration	Y	
4	Core	Change Configuration	Y	
5	Core	Heartbeat	Y	
6	Core	Charging Session - Local - Plugin first	Y	
7	Core	Charging Session - Local - Identification first - Connection Loss	Y	
8	Core	Charging session - Local - Identification first - Connection TimeOut	Y	
9	Core	Hard Reset - During Charging session	Y	<ul style="list-style-type: none">• Charger sent 'Stop Transaction' after reboot. It is preferable that we should receive a "Stop Transaction" BEFORE rebooting.• Charge Point Status doesn't change to "Unavailable" before it reboots.
10	Core	Hard Reset - No charging session	Y	<ul style="list-style-type: none">• Charge Point Status doesn't change to "Unavailable" before it reboots.
11	Core	Soft Reset - During Charging session	Y	<ul style="list-style-type: none">• Charge Point Status doesn't change to "Unavailable" before it reboots.
12	Core	Soft Reset - No charging session	Y	<ul style="list-style-type: none">• Charge Point Status doesn't change to "Unavailable" before it reboots.
13	Core	Charging session - Local - Unauthorized	Y	
14	Core	Charging session - Remote Start and Stop Transaction - Cable first	Y	
15	Core	Charging session - Remote Start Transaction - Request first - Unlock Connector	Y	
16	Core	Hardware related notification / error condition	Y	
17	Firmware Management	Remote Firmware update - Download failed	Y	<ul style="list-style-type: none">• The firmware file was sent from a HTTPS location (https://) which was shared by operator.
18	Firmware Management	Remote Firmware update - Installation failed	Y	
19	Firmware Management	Remote Firmware update - Download & install	Y	
20	Firmware Management	Remote get diagnostics report	Y	
21	Firmware Management	Remote get diagnostics - fail	Y	
22	Core	Clear cache	Y	
23	Remote Trigger	TriggerMessage	Y	