

# Congratulations, you're certified!

You are now guaranteed compatibility with  
the GreenFlux eMobility platform.

greenflux



Model:

Duo Smart

Firmware version:

1.8.0

AC/DC:

AC

Certification date:

26-01-2026

Certification level:

- OCPP 1.6 JSON
- OCPP 2.0.1 Core
- Smart Charging 1.6 JSON
- Eichrecht



**for Charge Stations connected to GreenFlux Platform using OCPP1.6 via JSON**

**Manufacturer Name: Eldon**

**Hardware model: DUO**

**Firmware 1.8.0**

**Tester: Mohanad Elsawy**

**Date: 1/26/2026**

Step	OCPP Profile	Action	Pass	Remarks
Step	OCPP Profile	Action	Pass	Remarks
1	Core	Boot charging station	✓	- Does not send ICCID and IMSI
2	Core	Change availability	✓	
3	Core	Get Configuration	✓	
4	Core	Change Configuration	✓	
5	Core	Heartbeat	✓	
6	Core	Charging Session - Local - Plugin first	✓	- To stop charging via RFID need to set PresentingRFIDEndCharging=True
7	Core	Charging Session - Local - Identification first - Connection Loss		- WebSocketPingTimeout should be larger than WebSocketPingInterval or the charger will fail to connect back
8	Core	Charging session - Local - Identification first - Connection TimeOut	✓	
9	Core	Hard Reset - During Charging session	✓	- Goes to Preparing instead of Finishing after reboot
10	Core	Hard Reset - No charging session	✓	
11	Core	Soft Reset - During Charging session	✓	- Goes to Preparing instead of Finishing after reboot
12	Core	Soft Reset - No charging session	✓	
13	Core	Charging session - Local - Unauthorized	✓	
14	Core	Charging session - Remote Start and Stop Transaction - Cable first	✓	
15	Core	Charging session - Remote Start Transaction - Request first - Unlock Connector	✓	
16	Core	Hardware related notification / error condition	✓	
17	Firmware Management	Remote Firmware update - Download failed	✓	
18	Firmware Management	Remote Firmware update - Installation failed	✓	- If the link does not have the right extension(.raucb) it

Step	OCPP Profile	Action	Pass	Remarks
19	Firmware Management	Remote Firmware update - Download & install	✓	
20	Firmware Management	Remote get diagnostics report	✓	
21	Firmware Management	Remote get diagnostics - fail	✓	
22	Core	Clear cache	✓	
23	Remote Trigger	TriggerMessage	✓	- Diagnostic Status not implemented -FirmwareStatus not implemented