

# Congratulations, you're certified!

You are now guaranteed compatibility with  
the GreenFlux eMobility platform.

greenflux



Model:

Ampax

Firmware version:

1.0.18

AC/DC:

DC

Certification date:

05-03-2026

Certification level:



OCPP 1.6 JSON



OCPP 2.0.1 Core



Smart Charging 1.6 JSON



Eichrecht



## for Charge Stations connected to GreenFlux Platform using OCPP1.6 via JSON

**Manufacturer Name: Injet**

**Hardware model: AMPAX**

**Firmware 1.0.18**

**Tester: Mohanad Elsayy**

**Date: 3/5/2026**

Step	OCPP Profile	Action	Pass	Remarks
Step	OCPP Profile	Action	Pass	Remarks
1	Core	Boot charging station	✓	- Does not send IMSI or ICCID when connected via SIM
2	Core	Change availability	✓	
3	Core	Get Configuration	✓	
4	Core	Change Configuration	✓	
5	Core	Heartbeat	✓	
6	Core	Charging Session - Local - Plugin first	✓	- When you swipe an invalid card the charger does not send an Invalid Authorization message. However, it continues charging as expected
7	Core	Charging Session - Local - Identification first - Connection Loss	✓	- Does not support Identification first
8	Core	Charging session - Local - Identification first - Connection TimeOut	✓	- Only works with RemoteStart as the charger does not support Swiping a card while it is unplugged
9	Core	Hard Reset - During Charging session	✗	- Sends stop transaction after the reboot. Need it to be sent before - Sends Preparing instead of Finishing - Does not send unavailable status notification before reboot
10	Core	Hard Reset - No charging session	✓	
11	Core	Soft Reset - During Charging session	✓	- Does not send unavailable status notification before reboot
12	Core	Soft Reset - No charging session	✓	
13	Core	Charging session - Local - Unauthorized	✓	
14	Core	Charging session - Remote Start and Stop Transaction - Cable first	✓	
15	Core	Charging session - Remote Start Transaction - Request first - Unlock Connector	✓	- Unlock connector does not work as it's a DC charger
16	Core	Hardware related notification / error condition	✓	
17	Firmware Management	Remote Firmware update - Download failed	N/A	The Manufacturer performs the updates for the customers
18	Firmware Management	Remote Firmware update - Installation failed		

Step	OCPP Profile	Action	Pass	Remarks
19	Firmware Management	Remote Firmware update - Download & install		
20	Firmware Management	Remote get diagnostics report	✓	
21	Firmware Management	Remote get diagnostics - fail	✓	
22	Core	Clear cache	✓	
23	Remote Trigger	TriggerMessage	✓	