Congratulations, you're certified!

You are now guaranteed compatibility with the GreenFlux eMobility platform.

greenflux

INJET
Energizing Evolution

Model:

Ampax

Firmware version:

1.0.18

AC/DC:

DC

Certification date:

05-03-2026



Certication level:

- [x] OCPP 1.6 JSON
- [ ] OCPP 2.0.1 Core
- [ ] Smart Charging 1.6 JSON
- [ ] Eichrecht

for Charge Stations connected to GreenFlux Platform using OCPP1.6 via JSON

Manufacturer Name: Injet

Hardware model: AMPAX

Firmware 1.0.18

Tester: Mohanad Elsawy

Date: 3/5/2026

Step	OCPP Profile	Action	Pass	Remarks
Step	OCPP Profile	Action	Pass	Remarks
1	Core	Boot charging station	✔	- Does not send IMSI or ICCID when connected via SIM
2	Core	Change availability	✔	
3	Core	Get Configuration	✔	
4	Core	Change Configuration	✔	
5	Core	Heartbeat	✔	
6	Core	Charging Session - Local - Plugin first	✔	- When you swipe an invalid card the charger does not send an Invalid Authorization message. However, it continues charging as expected
7	Core	Charging Session - Local - Identification first - Connection Loss	✔	- Does not support Identification first
8	Core	Charging session - Local - Identification first - Connection TimeOut	✔	- Only works with RemoteStart as the charger does not support Swiping a card while it is unplugged
9	Core	Hard Reset - During Charging session	✘	- Sends stop transaction after the reboot. Need it to be sent before - Sends Preparing instead of Finishing - Does not send unavailable status notification before reboot
10	Core	Hard Reset - No charging session	✔	
11	Core	Soft Reset - During Charging session	✔	- Does not send unavailable status notification before reboot
12	Core	Soft Reset - No charging session	✔	
13	Core	Charging session - Local - Unauthorized	✔	
14	Core	Charging session - Remote Start and Stop Transaction - Cable first	✔	
15	Core	Charging session - Remote Start Transaction - Request first - Unlock Connector	✔	- Unlock connector does not work as it's a DC charger
16	Core	Hardware related notification / error condition	✔	
17	Firmware Management	Remote Firmware update - Download failed	N/A	The Manufacturer performs the updates for the customers
18	Firmware Management	Remote Firmware update - Installation failed		

Step	OCPP Profile	Action	Pass	Remarks
19	Firmware Management	Remote Firmware update - Download & install		
20	Firmware Management	Remote get diagnostics report	✔	
21	Firmware Management	Remote get diagnostics - fail	✔	
22	Core	Clear cache	✔	
23	Remote Trigger	TriggerMessage	✔	