

Congratulations, you're certified!

You are now guaranteed compatibility with
the GreenFlux eMobility platform.

greenflux



CTEK

Model:

Chargestorm Connected 3

Firmware version:

R4.11.7-0-g33741361b

AC/DC:

AC

Certification date:

31-03-2026

Certification level:

- OCPP 1.6 JSON
- OCPP 2.0.1 Core
- Smart Charging 1.6 JSON
- Eichrecht



for Charge Stations connected to GreenFlux Platform using OCPP1.6 via JSON

Manufacturer Name: CTEK E-Mobility AB

Hardware model: CS Connected v3

Firmware r4.9.4-0-g196eb07b

Tester: Malgorzata Guzel

Date: 22/01/2026

Step	OCPP Profile	Action	Pass	Remarks
Step	OCPP Profile	Action	Pass	Remarks
1	Core	Boot charging station	✓	- No simcard option
2	Core	Change availability	✓	
3	Core	Get Configuration	✓	
4	Core	Change Configuration	✓	
5	Core	Heartbeat	✓	
6	Core	Charging Session - Local - Plugin first	✓	- It failed the first time. The authMode was changed to 1, and afterwards it charged, but I didn't see the authorization message. - The connector status switches to Suspended EV before switching to Charging.
7	Core	Charging Session - Local - Identification first - Connection Loss	✓	- The connector status switches to Suspended EV before switching to Charging. - Auth message was not visible in the portal
8	Core	Charging session - Local - Identification first - Connection TimeOut	✓	
9	Core	Hard Reset - During Charging session	✓	- The configuration key resetResume is set to true, so the charger will resume the charging session once it comes back online.
10	Core	Hard Reset - No charging session	✓	
11	Core	Soft Reset - During Charging session	✓	- The configuration key resetResume is set to true, so the charger will resume the charging session once it comes back online.
12	Core	Soft Reset - No charging session	✓	
13	Core	Charging session - Local - Unauthorized	✓	
14	Core	Charging session - Remote Start and Stop Transaction - Cable first	✓	
15	Core	Charging session - Remote Start Transaction - Request first - Unlock Connector	✓	
16	Core	Hardware related notification / error condition	✓	

Step	OCP Profile	Action	Pass	Remarks
17	Firmware Management	Remote Firmware update - Download failed	✓	- Retries and RetryInterval must have values.
18	Firmware Management	Remote Firmware update - Installation failed	✓	
19	Firmware Management	Remote Firmware update - Download & install	✓	
20	Firmware Management	Remote get diagnostics report	✓	
21	Firmware Management	Remote get diagnostics - fail	✓	
22	Core	Clear cache	✓	
23	Remote Trigger	TriggerMessage	✓	- The TriggerMessage for BootNotification is not supported.