

Test Report for Charge Stations connected to GreenFlux Platform using OCPP1.6 via JSON	
Manufacturer Name:	StarCharge
Hardware model:	Artemis - 7-22kW
Firmware	Shell2.0.1.3b121
Tester:	Ali Kodamy
Date:	6/4/2024

Step	OCPP Profile	Action	Timestamp	Pass	Remarks
1	Core	Boot charging station	2024-06-04 13Y		
2	Core	Change availability	2024-06-04 13Y		
3	Core	Get Configuration	2024-06-04 13Y		
4	Core	Change Configuration	2024-06-04 13Y		
5	Core	Heartbeat	2024-06-04 13Y		
6	Core	Charging Session - Local - Plugin first	2024-06-04 14Y		It does not display an invalid message on the portal after swiping
7	Core	Charging Session - Local - Identification first - Connection Loss	2024-06-04 14Y		
8	Core	Charging session - Local - Identification first - Connection TimeOut	2024-06-04 14Y		
9	Core	Hard Reset - During Charging session	2024-06-04	Y	- Goes to "Preparing" instead of "Finishing" after the reboot is done - The status update notification "unavailable" is not triggered before the restart is committed.
10	Core	Hard Reset - No charging session	2024-06-04 14Y		The status update notification "unavailable" is not triggered before the restart is committed.
11	Core	Soft Reset - During Charging session	2024-06-04 14Y		
12	Core	Soft Reset - No charging session	2024-06-04 14Y		
13	Core	Charging session - Local - Unauthorized	2024-06-04 14Y		
14	Core	Charging session - Remote Start and Stop Transaction - Cable first	2024-06-04 14Y		
15	Core	Charging session - Remote Start Transaction - Request first - Unlock Connector	2024-06-04 15Y		
16	Core	Hardware related notification / error condition	2024-06-04 15Y		
17	Firmware Management	Remote Firmware update - Download failed	2024-06-04	Y	
18	Firmware Management	Remote Firmware update - Installation failed	2024-06-04	Y	
19	Firmware Management	Remote Firmware update - Download & install	2024-06-04	Y	The status update notification "unavailable" is not triggered before the restart is committed.
20	Firmware Management	Remote get diagnostics report	2024-06-04	Y	
21	Firmware Management	Remote get diagnostics - fail	2024-06-04	Y	
22	Core	Clear cache	2024-06-04 15Y		
23	Remote Trigger	TriggerMessage	2024-06-04 15Y		