

Test Report for Charge Stations connected to GreenFlux Platform using OCPP1.6 via JSON	
Manufacturer Name:	KREISEL Electric
Hardware model:	CHIMERO_D5_180
Firmware	3.1.1
Tester:	Ali Kodamy
Date:	9/11/2024

Step	OCPP Profile	Action	Timestamp	Pass	Remarks
1	Core	Boot charging station	2024-09-11	Y	
2	Core	Change availability	2024-09-11	Y	
3	Core	Get Configuration	2024-09-11	Y	
4	Core	Change Configuration	2024-09-11	Y	- Current.Offered is not supported
5	Core	Heartbeat	2024-09-11	Y	
6	Core	Charging Session - Local - Plugin first	2024-09-11	Y	- After swiping the RFID to stop the charging session, we received the status update "Suspended EVSE" before receiving the "Finishing" status notification.
7	Core	Charging Session - Local - Identification first - Connection Loss	2024-09-11	Y	- While the charger was offline, after swiping the RFID to stop the charging session, we received the "Suspended EVSE" status update before receiving the "Finishing" status notification.
8	Core	Charging session - Local - Identification first - Connection TimeOut	2024-09-11	Y	
9	Core	Hard Reset - During Charging session	2024-09-11	Y	
10	Core	Hard Reset - No charging session	2024-09-11	Y	
11	Core	Soft Reset - During Charging session	2024-09-11	Y	
12	Core	Soft Reset - No charging session	2024-09-11	Y	
13	Core	Charging session - Local - Unauthorized	2024-09-11	Y	
14	Core	Charging session - Remote Start and Stop Transaction - Cable first	2024-09-11	Y	- After sending the Stop Transaction command, we received the status update "Suspended EVSE" before receiving the "Finishing" status notification.
15	Core	Charging session - Remote Start Transaction - Request first - Unlock Connector	2024-09-11	NA	- DC charger
16	Core	Hardware related notification / error condition	2024-09-11	Y	
17	Firmware Management	Remote Firmware update - Download failed	2024-09-11	Y	
18	Firmware Management	Remote Firmware update - Installation failed	2024-09-11	Y	
19	Firmware Management	Remote Firmware update - Download & install	2024-09-11	Y	
20	Firmware Management	Remote get diagnostics report	2024-09-11	Y	
21	Firmware Management	Remote get diagnostics - fail	2024-09-11	Y	
22	Core	Clear cache	2024-09-11	NA	- Not supported
23	Remote Trigger	TriggerMessage	2024-09-11	N	- MeterValue TriggerMessage is not supported yet