

# Congratulations, you're certified!

You are now guaranteed compatibility with  
the GreenFlux eMobility platform.

greenflux



## Starcharge Titan V3

Model:

Titan V3

Firmware version:

1.3025.7

AC/DC:

DC

Certification date:

07-02-2024

Certification level:

- OCPP 1.6 JSON
- OCPP 2.0.1 Core
- Smart Charging 1.6 JSON
- Eichrecht



## for Charge Stations connected to GreenFlux Platform using OCPP1.6 via JSON

**Manufacturer Name: StarCharge**

**Hardware model: Jupiter V3**

**Firmware 1.3013.1**

**Tester: Wei Wang**

**Date: 2/7/2026**

| Step | OCPP Profile        | Action   | Pass | Remarks   |
|------|---------------------|--|------|---|
| Step | OCPP Profile        | Action   | Pass | Remarks   |
| 1    | Core                | Boot charging station  | ✓    |   |
| 2    | Core                | Change availability  | ✓    |   |
| 3    | Core                | Get Configuration  | ✓    |   |
| 4    | Core                | Change Configuration   | ✓    |   |
| 5    | Core                | Heartbeat  | ✓    |   |
| 6    | Core                | Charging Session - Local - Plugin first  | ✓    | * The charger only supports plugin first for Identification.                                    |
| 7    | Core                | Charging Session - Local - Identification first - Connection Loss              | ✓    | * See Step 6. This implementation is acceptable.  |
| 8    | Core                | Charging session - Local - Identification first - Connection TimeOut           | N/A  | * ConnectionTimeOut Implements for Remote Start Transaction                                     |
| 9    | Core                | Hard Reset - During Charging session   | ✓    |   |
| 10   | Core                | Hard Reset - No charging session   | ✓    |   |
| 11   | Core                | Soft Reset - During Charging session   | ✓    |   |
| 12   | Core                | Soft Reset - No charging session   | ✓    |   |
| 13   | Core                | Charging session - Local - Unauthorized  | ✓    |   |
| 14   | Core                | Charging session - Remote Start and Stop Transaction - Cable first             | ✓    |   |
| 15   | Core                | Charging session - Remote Start Transaction - Request first - Unlock Connector | ✓    | * The charger has 2 DC connectors and 1 AC connectors, Unlock Connector works for AC connector. |
| 16   | Core                | Hardware related notification / error condition                                | ✓    |   |
| 17   | Firmware Management | Remote Firmware update - Download failed                                       | ✓    |   |
| 18   | Firmware Management | Remote Firmware update - Installation failed                                   | ✓    | * Received DownloadedFailed instead of InstallationFailed.                                      |
| 19   | Firmware Management | Remote Firmware update - Download & install                                    | ✓    |   |
| 20   | Firmware Management | Remote get diagnostics report  | ✓    |   |

| Step | OCPP Profile        | Action                        | Pass | Remarks |
|------|---------------------|-------------------------------|------|---------|
| 21   | Firmware Management | Remote get diagnostics - fail | ✓    |         |
| 22   | Core                | Clear cache                   | ✓    |         |
| 23   | Remote Trigger      | TriggerMessage                | ✓    |         |

**for Charge Stations connected to GreenFlux Platform using OCPP1.6 via JSON**

**Manufacturer Name: StarCharge**

**Hardware model: Titan V3**

**Firmware 1.3025.7**

**Date: 2/23/2026**

| <b>1</b> | <b>Smart Charging</b> | <b>Send 2 Charging Profiles &amp; Validate Metervalues</b> | <b>Y</b> |
|----------|-----------------------|--|----------|
| 1        | Smart Charging        | Send 2 Charging Profiles & Validate Metervalues            | ✓        |
| 2        | Smart Charging        | Verify TxDefaultProfiles                                   | ✓        |
| 3        | Smart Charging        | Clear ChargingProfiles                                     | ✓        |